
## **Optical Connector Cleaner NEOCLEAN-EZ User's Manual**

Thank you for choosing to use the "NEOCLEAN-EZ" optical connector cleaner. This product is a "penshaped" optical connector cleaner that enables you to clean optical connector ferrule end face with a simple, one-push action. Please read this manual carefully to ensure proper use of this equipment.

## 1. Names and Descriptions of Parts



•Thread Remaining Confirmation Method When the thread has run out, a blue colored tape appears in the Thread Remaining Confirmation Window. One cleaner can be used for approximately 400 times.

Storage


Avoid storing in locations with high temperature and humidity.

2. Compatible Connectors

Product Name (Model No.)	Connector	Attachment Color
NEOCLEAN-EZ1[ATC-NE-EZ1]	MU、LC	White
NEOCLEAN-EZ2[ATC-NE-EZ2]	SC <sub>\</sub> FC	Orange

## 3. Method of Use

• Cleaning Optical Connector Ferrule End Face Inside an Adaptor





② Push in the slider. The cleaning is completed when the push action stops.



\* Extending the Tool The tool can be extended by inserting the attachment onto the back end of the slider.



Cleaning an Optical Connector Plug

①Remove the cap.

② Insert the plug into the hole of the tip on the front end. ③Push in the slider. The cleaning is completed when the push action stops.



\* NEOCLEAN is a trademark of NTT Advanced Technology Corporation.

 Inquiries
NTT Advanced Technology Corporation http://www.ntt-at.com/product/optical\_cleaner/



201801